Gartlein, C. W. Alternating current amplifier for astronomical photometry.

The National Geographic Society-Cornell University Study of Aurora has used photomultipliers with A.C. amplification methods regularly since 1941. By 1944, results were so promising that it seemed desirable to build the best equipment possible. The new amplifying set-up was completed early in 1945 and modified some since then.

The incoming light is chopped at 330 cycles before entering the photomultiplier and the output current fed into a 330 cycle push pull amplifier (Goldberg circuit) having band width of 20 cycles and a maximum gain of one million. The output is rectified, filtered and put through a D.C. impedance matching amplifier into a Leeds and Northrup or Esterline-Angus recorder.

Response is linear within a few per cent and constant over periods up to eight hours, even though this is all operated from A.C.

It is believed this type of circuit offers advantages over other circuits for astronomical use except in those cases where linearity is the prime requisite or where the photomultiplier tubes will be refrigerated. It would appear that this method allows fainter stars to be measured without refrigeration of the cell. It also allows the use of cells so noisy or having leakage currents so high that they cannot be used on D.C. amplification. One of these amplifiers is now being used by Dr. E. F. Carpenter of the Steward Observatory.

*Cornell University,
Ithaca, N. Y.*

Green, Louis C. Wave functions with I.B.M. equipment.

Under an Office of Naval Research contract administered by Yale University an effort has been made to apply International Business Machine equipment to the computation of atomic wave functions. Through the courtesy of the I.B.M. Company this work has been carried on at the Watson Laboratory. Staff members of the Laboratory have been most cooperative and helpful, especially Miss Eleanor Krawitz.

A board for the integration of the radial part of the Schrodinger equation has been designed, built, and used on the relay calculators. This board enables the machine to compute a wave function for a given set of parameters in about ten minutes. This is approximately 150 times as fast as a solution of the same accuracy could be

obtained by hand. A deck of master cards must be prepared ahead. On these are punched the atomic field and certain instructions, primarily those for interval change. The master deck is introduced in the read feed of the relay calculators. The energy and angular momentum parameters are entered through hand-set switches. The same master deck is used until there is cause to change the atomic field. A deck of blank cards is introduced into the punch feed and the integration proceeds. Both interval change and integration procedures are good to sixth differences. Six or more figures are carried throughout. Allowance is made for the rapid growth of the wave functions for large values of the angular momentum, so that one procedure is applicable to all cases. No change whatever in the instructions to the machine is necessary if exchange is to be included. However, the exchange terms must be precomputed. They may be punched in either the master deck or the blank deck, the choice being made on the basis of the particular program of the moment. Not only the function but also its first and second derivatives and certain auxiliary quantities are punched. This information enables rapid computation of the dipole moment, momentum, and acceleration as part of the program of testing the probable physical reality of the results. It also aids effective numerical checking. At most, the deck on which the wave functions appear will require three handlings, one each for punching exchange, computing, and checking. Results of the first run of the machine, on *Ca II*, are being worked up at present.

*Strawbridge Observatory,
Haverford College,
Haverford, Pa.*

Hagen, John P. A study of the effect of the solar atmosphere on the emission of short radio waves.

The monochromatic effective temperature of the quiet sun measured at radio wave lengths varies between the limits of 6700°K at 8 mm wave length to 10⁶ degrees K at 200 cm wave length. This is to be expected when the opacity of the sun's atmosphere at radio wave lengths is considered and when a proper temperature distribution for the corona and chromosphere is assigned.

The opacity of the solar atmosphere for the various radio wave lengths was computed, the coefficient of absorption being a function of the electron density, the wave length, the temperature, and the refractive index of the gas according